



AMPLIFIERS

MA 2X100

Music amplifier



MA 2X100 amplifier

Brand new AMC MA 2X100 2-channel mixer amplifier. Could be used in 100V 2-channel operation and low impedance stereo mode operation. Integrated subwoofer output for background music applications.

MA 2X100 stereo music amplifier has 3 unbalanced RCA input pairs and 3 balanced "XLR" microphone inputs. Apart from two 100V speaker outputs **MA 2X100** has two 8 Ohm speaker outputs via binding posts and RCA line outputs for subwoofer which enables active a passive subwoofer connection. **MA 2X100** is perfect for a demanding background music and public address.

TECHNICAL SPECIFICATIONS

unit: mm

	MA 2x100
Output power	2 × 100W
AC power consumption	500 W
Outputs	8 Ω binding post, or 100 V 100 Ohm (Screw terminal)
Frequency response	50 Hz – 18 kHz
THD	Less than 0,05% at 1 kHz, rated power
Signal/noise ratio	70 dB below rated power
Damping factor	> 400
Controls	Input gain control (rear panel)
Protection	Speaker short, temperature, overload
Power supply	AC 115V/ 230V, 50 Hz ±10%; DC 24 V (max 10% deviation)
Weight	9 kg
Dimensions	88 mm × 425 mm × 305 mm
Color	Black
Mounting options	Table top or 19" rack mountable